

Hot models - LG handset (demonstration with LG P7200)

GPRS setting

1. Press “Menu” to enter main menu → select “Browser” → “Settings” → “Profiles” → any profile to be edited → Press “Options” key → “Add new”.
2. Follow below table and enter the parameters. Press “OK” key when completed.

Profile name	CSL Prepaid GPRS
---------------------	------------------

3. Select the profile `CSL Prepaid GPRS` to be edited → Press “Options” key → “Settings” → Follow below table and enter the parameters. Press “OK” key when completed.

Homepage	http://192.168.58.230/prepaid/index.jsp	
Bearer	GPRS	
GPRS settings	APN	cslp1
	User ID	Please leave it blank
	Password	Please leave it blank
Proxy settings	Proxy	On
	IP address	192.168.59.51
	Port	9201
DNS settings	Please leave it blank	

4. Scroll to select the `CSL Prepaid GPRS` profile set to default → Press “Options” key → “Activate”.

MMS setting

1. Press “Menu” to enter main menu → select “Messages” → “Settings” → “Multimedia message” → “Network settings” → any profile to be edited → Press “Options” key → “Add new”.
2. Follow below table and enter the parameters. Press “OK” key when completed.

Profile name	CSL Prepaid MMS
---------------------	-----------------

3. Select “CSL MMS” → Press “Options” key → “Settings” → Follow below table and enter the parameters. Press “OK” key when completed.

Homepage	http://mms.hkcs1.com:8002	
Bearer	GPRS	
GPRS settings	APN	cslp1
	Username	Please leave it blank
	Password	Please leave it blank
Proxy settings	Proxy settings	On
	IP address	192.168.59.51
	Port	9201
DNS settings	Please leave it blank	

4. When finish, select “[CSL Prepaid MMS](#)” → Press ‘[Options](#)’ key → “[Activate](#)”.
5. Press “[Back](#)” to return “[Multimedia message](#)” → Follow below table and enter the parameters.

Priority	Normal
Validity period	Maximum
Subject	On
Delivery report	No
Auto retrieve	On
Permitted message types	<input checked="" type="checkbox"/> Personal <input checked="" type="checkbox"/> Advertisements <input checked="" type="checkbox"/> Information

6. Press ‘[Save](#)’ key → Press “[Back](#)” to exit.