

Hot model - Motorola handset (Demonstration with Motorola V3x)

GPRS setting

Press 'Navigation' key, select 'WebAccess' -> 'Web Sessions' -> press 'Options' key and create new profile:

Web Session name	CSL Prepaid GPRS
Homepage	http://192.168.58.230/prepaid/index.jsp
Server type 1	HTTP
Gateway IP 1	192.168.59.51
Port 1	8080
GPRS APN	cslp1

MMS setting

Press 'Navigation' key, select 'Messages' -> press 'Options' key and enter 'Setup' -> select 'Message Set Up' -> 'Multimedia Msg Set Up' and create new profile:

Web Session name:	CSL Prepaid MMS
Server type 1	WAP
Gateway IP 1	192.168.59.51
Port 1:	9201
GPRS APN	cslp1
MMSC Server name	http://mms.hkcs1.com:8002