

Hot models - Sharp handset (demonstration with Sharp 833)

GPRS setting

1. Press “Centre key” enter main menu -> select “Connectivity” → “Internet Settings” → “APN Settings” → “CreateNew”.
2. Input the following parameters in table:

Access Point Name	cslp1
APN	cslp1
Authentication Type	NONE
User Name	Please leave it blank
Password	Please leave it blank
DNS	Please leave it blank
Linger Time	180

3. Press “Options” and then select “Set” to save the setting.
4. Press “Back” return to “Internet Settings” sub menu, then select “Proxy Settings” → “CreateNew”.
5. Input the following parameters in table:

Proxy Name	CSL Prepaid GPRS
Proxy Address	192.168.59.51
Access Point	cslp1
Home	http://192.168.58.230/prepaid/index.jsp
Port Number	8080
Authentication Type	HTTP-BASIC
User Name	Please leave it blank
Password	Please leave it blank

6. Press “Options” and then select “Set” to save the setting.
 7. Press “Back” return to “Internet Settings” sub menu, then select “ WAP Settings” → “CreateNew”.
 8. Input the following parameters in table:
- | | |
|---------------------|------------------|
| Profile Name | CSL Prepaid GPRS |
| Proxy | CSL Prepaid GPRS |
| Use Proxy | On |
9. Press “Options” and then select “Set” to save the setting.
 10. Highlight “CSL Prepaid GPRS”, press “Options” and then select “Activate” to set as default profile.
 11. When completed, press “End call” to exit.

MMS setting

1. Press “Centre key” to enter main menu -> select “Messages” → “Messaging Settings” → “MMS Settings” → “MMS Accounts” → “CreateNew”.

2. Input the following parameters in table:

Profile Name	CSL Prepaid MMS
Proxy	CSL Prepaid GPRS
Relay ServerURL	http://mms.hkcs1.com:8002

3. Press “Options” and then select “Set” to save the setting.
4. Highlight “CSL Prepaid MMS”, press “Options” and then select “Activate” to set as default profile.

5. Press “[Back](#)” until return to “**Messaging Settings**” submenu, and then select “[General Settings](#)”.
6. Input the following parameters in table:

Home Download	Always download
Intl. Download Msg.	Always download

7. When completed, press “[End call](#)” to exit.