Hot models - Samsung handset (demostration with SGH-Z508)

GPRS setting

- Press "Menu" to enter main menu -> select "Settings" → "Connectivity" → "Connections"
 → any profile to be edited → Press "Select"
- 2. Follow below table to enter the parameters. When finish, press "Save" to save the setting

Set name	CSL Preapid GPRS	
Access name	cslp1	
Auth type	Normal	
User ID	Leave it blank	
Password	Leave it blank	
Protocol	HTTP	
Home URL	http://192.168.58.230/prepaid/index.jsp	
Proxy address	192.168.59.51	
Port	8080	
Linger time (sec.)	300	

- 3. Pres "Back" until return to main menu, then select "Internet" → "Network settings" → Select "CSL Preapid GPRS".
- 4. When finish, press "End call" key to exit.

MMS setting

- Press "Menu" to enter main menu -> select "Settings" → "Connectivity" → "Connections"
 → any profile to be edited → Press "Select".
- 2. Follow below table to enter the parameters. When finish, press "Save" to save the setting

Set nameCSL Prepaid MMSAccess namecslp1Auth typeNormalUser IDLeave it blankPasswordLeave it blankProtocolWAPHome URLhttp://mms.hkcsl.com:8002Gateway address192.168.59.51			
Access namecslp1Auth typeNormalUser IDLeave it blankPasswordLeave it blankProtocolWAPHome URLhttp://mms.hkcsl.com:8002Gateway address192.168.59.51	Set name	CSL Prepaid MMS	
Auth typeNormalUser IDLeave it blankPasswordLeave it blankProtocolWAPHome URLhttp://mms.hkcsl.com:8002Gateway address192.168.59.51	Access name	cslp1	
User IDLeave it blankPasswordLeave it blankProtocolWAPHome URLhttp://mms.hkcsl.com:8002Gateway address192.168.59.51	Auth type	Normal	
PasswordLeave it blankProtocolWAPHome URLhttp://mms.hkcsl.com:8002Gateway address192.168.59.51	User ID	Leave it blank	
ProtocolWAPHome URLhttp://mms.hkcsl.com:8002Gateway address192.168.59.51	Password	Leave it blank	
Home URLhttp://mms.hkcsl.com:8002Gateway address192.168.59.51	Protocol	WAP	
Gateway address 192.168.59.51	Home URL	http://mms.hkcsl.com:8002	
	Gateway address	192.168.59.51	
Secure connection Off	Secure connection	Off	
Linger time (sec.) 300	Linger time (sec.)	300	

3. Pres "Back" until return to main menu, then select "Messages" \rightarrow "Settings" \rightarrow "Multimedia message".

Sending options	Priority	Normal	
	Expiration	Custom time	
	Custom time (Hour)	72	
	Delivery	Immediately	
Receiving options	Home network	Auto download	
	Roaming network	Auto download	
	Send delivery report		
	Send read report		
	Reject anonymous		
	Reject advertisement		
MMS profiles		CSL Prepaid MMS	
Message size		300 KB	

4. Follow below table and enter the parameters. When finish, press "Save" to store the setting.

5. When finish, press "Back" to exit.